

## Tech specs

EN54 LINE

# EN54 FireProtect (Smoke) Jeweller

Wireless addressable point smoke detector



Device compatibility

Check

---

## Communication

## Jeweller communication technology

Proprietary wireless communication technology to transmit commands, alarms, and events.

Key features:

- Two-way communication.
- Advanced sabotage protection.
- Block encryption featuring a dynamic key.
- Instant notifications.
- Remote control and configuration in Ajax apps.

Learn more 

### Frequency bands

866.0–866.5 MHz

868.0–868.6 MHz

868.7–869.2 MHz

905.0–926.5 MHz

915.85–926.5 MHz

921.0–922.0 MHz

Depends on the sales region.

### Maximum effective radiated power (ERP)

up to 20 mW

Automatic power control to reduce power consumption and radio interference.

### Radio signal modulation

GFSK

### Radio communication range

up to 1,700 m

Between the device and control and indicating equipment (CIE) or a range extender in an open space.

**Calculate radio communication range at the facility** ➤

## **Encrypted communication**

All stored and transmitted data is protected by block encryption featuring a dynamic key.

## **Frequency hopping**

To prevent radio interference and jamming.

**Learn more** ➤

---

## **Smoke detection**

### **Sensitive element**

dual-spectrum optical sensor

Detects smoke based on the size of particles in the air.

### **False alarm protection**

The device does not respond to water vapor.

### **Patented smoke chamber**

Protects the smoke sensor from dust, dirt, and insects.

---

## Additional features

### LED indication

- red
- yellow
- green

For indicating detector states: fire alarm, functionality testing, etc.

## Installation recommendations

The device is designed for indoor use only.

The SmartBracket mounting panel allows the detector to be rotated up to 90° even after installation.

## Sabotage protection

### Tamper button

Fault notification when an attempt is made to remove the device from the mounting panel.

Learn more [➤](#)

### Lock for SmartBracket

to secure the device on the SmartBracket mounting panel

When locked, the lock secures the device and prevents it from being removed without a special tool.



### Protection against spoofing

device authentication

### Connection loss detection

after 36 s

Detection time depends on **Jeweller** settings.

---

## Power supply

### Battery

2 × CR123A

Pre-installed.

### Tool-free battery replacement

To replace the batteries, open the lids of the battery compartments.



### Reverse polarity protection

Prevents device damage if the batteries are put in incorrectly.

### Recommended battery type

Huiderui CR123A; 3 V; 1,600 mAh,  
LiMnO<sub>2</sub>

### Calculated battery life

up to 6 years

---


## Enclosure

### Dimensions

124 × 124 × 48 mm

### Weight

281 g



### Operating temperature range

from 0 °C to +50 °C

### Operating humidity

up to 80%



### Protection class

IP20

### Flammability rating

UL 94 V-0

---

## Color

Black

White



---

## Complete set

EN54 FireProtect (Smoke) Jeweller

SmartBracket mounting panel

2 × CR123A battery (pre-installed)

Installation kit

Quick start guide

---

## Revision

1

## Certification and compliance with standards



EN54 FireProtect (Smoke) Jeweller

