

DS-PS102X Wired External Sounder



The wired sounder is used to connect to wired control panel, can be controlled by PGM/BELL port from panel. The sounder can alarm up to 105dB sound. The sounder can be used both internal or external, the LED flash and the sounder indication can be configured separately.

- Sound Decibel: 1 meter Single frequency point 110 dBA(Maximum value) Single frequency point 106 dBA(Average value)
- IP55 protective level
- Sound and LED flash indication separately
- Controlled by PGM/BELL port
- Three types of alarm sounds are available: fire alarm, panic alarm, and intrusion alarm.
- Triggered by Positive / Negative
- Tamper Alarm & Cut Wire Alarm

▪ Specification

Hardware features	
Tamper-Proof	Front cover tamper-proof Wall tamper-proof
Audio	
Sound pressure	110dB/1m (Maximum Value)
Electrical characteristics	
Power supply	9 to 16VDC
Typical voltage	12 VDC
Power consumption	Maximum current: 180mA@12V DC
Operation humidity	10% ~ 90%
Operation temperature	-20°C ~ + 60°C
General	
IP rate	IP55
Dimension(WxHxD)	221x215x51mm
Shell material	PC+ABS
Color	Red / Blue
Weight	475g

▪ Available Model

DS-PS102X/RED

DS-PS102X/BLUE

See Far, Go Further



www.hikvision.com
support@hikvision.com

