

Conventional Fire Alarm Panel



- 2 Fixed zones
- Up to 20 (32 SensoMag Series) fire detectors per zone
- Unlimited number of call points per fire zone

MAG2M is a conventional fire alarm panel certificated by EN54-2/4, providing 2 fixed zones. Up to 20 (32 SensoMAG Series) fire detectors can be connected to every fire zone. Unlimited number of call points can be connected to every of the fire zones.MAG2M is situated in a metal box with compact size. The panel is easy for installation and maintenance and provides user-friendly daily operation.The panel is suitable for residential, small and middle office applications with protected area up to 1000m .The panel is available in different language versions for the front panel.

Features

- 2 Fixed zones
- Up to 20 (32 SensoMag Series) fire detectors per zone
- Different language versions for the front panel
- Unlimited number of call points per fire zone
- Metal box

Technical Specifications

Main Power Supply	~230VAC ± 10%
Frequency	50/ 60Hz
Back-up Power Supply	1 battery, 12V/ 7Ah
Power Availability	0.7A
Main power supply fail consumption	50mA
Outputs (sounder circuits on the control PCB module)	24V/ 0.3A fuse
Output, FAULT Relay	3A@120VAC; 3A@60VDC
Output, FIRE Relay	3A@120VAC; 3A@60VDC
Relative humidity resistance	(93 ± 3)% @ 40°C
Weight (without battery)	2.7kg
Dimensions	200x290x80mm
Operational temperature range	0°C - +40°C

Last update: 11/2024